

RAS-PCI MODEM SETUP

From the prompt type # **swinstall**

Now note and enter the number of lines associated with **rasmodem**

You should now see "Installing rasmodem" type "n"

You should now see "Installing AT modem" type "n"

You should now be asked to "relink the kernal", type "y"

You should now be asked to "Boot by default", type "y"

You should now be asked to "rebuild the environment", type "y"

You should now reboot the system. After it comes up..

From the prompt type # **cd /abcconfigs**

From the prompt type # **te modemlist**

Once you are in the modemlist file, type the following...

tty1a (tab 1 time) Hays

(If your file appears similar to the above line... then hit **F-2 & X** to save and exit)

From the prompt type # **cd /etc/default**

From the prompt type # **te abcs**

Once you are in the abcs file type,

MODEMPORT=tty1a

(If your file appears similar to the above line... then hit **F-2**, then **X** to save and exit)

Now program your modem from the "**sysut**" menu. (If you have more than one modem, be sure to designate the proper address for the above modem "tty1a")

To setup the Internet dialup proceed with the following procedures...

From the prompt type # **swinstall**

Select the number of the item associated with "dialupinst"

After the installation is complete, follow these procedures

From the prompt type # **cd / (root)**

Now edit the file "startnet" & "stopnet" to read "**tty1a tty1A**"

From the prompt type # **cd /usr/lib/mstppp**

Now edit devices to **tty1a**

From the prompt type # **cd /** (you need to be in root)

From the prompt type # **startnet**

NOTE: Digifax is setup the same way but on port tty1b
Credit Card verification is the same using tty1c