

# FastComm 9642T LL Setup

Originating/answering modem when programming:

Up (on) 1 78  
Dn (off) 23456 90

Connect to terminal and issue this command:

For 9600 baud: AT&X2&N6&W  
For 4800 baud: AT&X2&N4&W

Then set the switches as indicated below originating modem:

Up (on) 234 678  
Dn (off) 1 5 90

Answering modem:

Up (on) 2 4 78  
Dn (off) 13 56 90

To force the modems to retrain, press IITDII on the answering modem.

if/usr/bin/calendar: syntax error at line N: 'end of file' unexpected" Error: NEW If this error is encountered in root's mail, solve it this way:

This problem is typically caused by a corrupted /etc/passwd file. To see if this is the case, edit /etc/passwd and look for a line with empty fields. This has been seen to be

```
< bad >:x:::::
```

which is a bogus line.

- save the /etc/passwd file before making changes
- Remove the bogus line in /etc/passwd
- Use lauthck -av1 to fix any problems that might still be there with the authorization databases, or because /etc/passwd does not match the authorization databases (if any questions are asked, answer them in the affirmative and re-run lauthck -av')
- Throw away the junk mail: mail

Use d[start]-[end] (specifying message numbers) to delete messages

Gm 01/26/02