

Installing Digifax Modem on Server Serial Port

(Digifax is already installed and set up in the software)

Materials:

- 1 – USR-Courier or 3COM modem
- 1 – 25pin male to 9pin female serial cable

1. At # type **faxconfig** and **enter**.
2. Choose **6** and **enter** for channels.
3. Choose **1** and **enter** for efax.
4. Choose **13** and **enter** for device name and type in **/dev/tty1a**.
5. Choose **Q** to quit and **enter**.
6. Choose **Q** to quit and **enter**, then **yes** to make changes permanent.
7. Now connect the 25 pin male side of the serial cable to the modem and the 9 pin female end to serial port 1 on your server.
8. Now on the server choose **Q** to quit and **Y** to restart server.
9. You should now have the ARQ/FAX light blinking on your modem.

NOTE: Make sure that **tty1a** and **tty1A** are disabled

GRN 02/28/02