

Installing Digifax Without A Faxcard

1. Type in (**swinstall**) [**enter**]
2. Choose **Digifax 290a** [**enter**]
3. Choose (**y**) for the ability to reboot after installation [**enter**]
4. [**enter**] when prompted
5. Dfax fax/1 and fax/2 , type (**n**) [**enter**]
6. Jfax- JT fax 9600 , type (**n**) [**enter**]
7. Bfax- Brooktrout TR111/112 , type (**n**) [**enter**]
8. Hpsj- HP Scanjet (Plus) , type (**n**) [**enter**]
9. Sjii- HP Scanjet lip/lic , type (**n**) [**enter**]
10. Enter a **device name** to modify, or **q** when done; type (**q**) [**enter**]
11. Type (**q**) [**enter**]
12. After confirmed , [**enter**]
13. Type (**q**) [**enter**]
14. After confirmed , [**enter**]
15. Type channel number to modify, type (**1**) [**enter**]
16. Choose (**1**) from menu [**enter**]
17. Type (**efax**) [**enter**]
18. Choose (**18**) from menu [**enter**]
19. Type (**USR-Courier**) [**enter**]
20. Type (**q**) [**enter**]
21. Choose (**13**) from menu [**enter**]
22. Type (**a02**) [**enter**]
23. Choose (**5**) [**enter**] [**y**] disable receive
24. Type (**q**) [**enter**]
25. Type (**q**) [**enter**]
26. Do you want to make these changes permanent? Type (**y**) [**enter**]
27. After confirmed, [**enter**]
28. Would you like to run /etc/faxconfig right now? Type (**y**) [**enter**]
29. Choose [**8**] server [**enter**]
30. Choose [**1**] enter # of retries[**1**]
31. Choose [**2**] wait period [**1**]
32. Make permanent [**y**]
33. Type (**q**) [**enter**]
34. Type (**l**) [**enter**]
35. Now reboot your system.
36. Make sure that the modem is plugged into the port when you boot up
37. Go to **sysut** and set up a printer in software

Printer id	Zfax
Description	fax doc software
Location	memory
[L]ocal [R]emote [T]ransparent	L
printer type	dumb
forms	fax
device, file or Spool command	/tmp/%temp
close	fax_digi /tmp/%temp; rm -f

- 38: Go to forms and printer configuration for POS and purchasing and set up the fax printer for workstations.

